7. Electrical Parts List

7-1 CS29M6HP8X/AWE

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY CHASSIS

1	*	AA91-01716E	ASSY CHASSIS;CS29M6HP8X/AWE	S.N.A
..2		AA96-20109C	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C300,KKP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA95-01787L	ASSY SUB-PCB,A/V SIDE;25,29M6,KS3APAL,AA	
...3	CN701	AA39-20068E	LEAD CONNECTOR-ASSY;,8P,YBNH025-08,67096	
...3	CN702	AA39-20070F	LEAD CONNECTOR-ASSY;,7P,YBNH025-07,67096	
...3	CN703	AA39-20069C	LEAD CONNECTOR-ASSY;,5P,YBNH025-05,67096	
...3	CN704	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,YBNH250-04,35184	
...3	CN705	AA39-20009D	LEAD CONNECTOR-ASSY;,1P,YFH800-01,500,16	
...3	JA701	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	JH701	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JS701	3722-001163	JACK-VHS;4P,12mm,AU,BLK,N	
...3		AA97-07089A	ASSY AUTO-A/V SIDE;25M6,KS3A,PAL,AA95-01	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C703	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
....4	C704	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
....4	C705	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
....4	C706	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
....4	C707	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	C708	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L704	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00345A	PCB-SIDE A/V;CS29K1,FR-1,1L,A,1.6T,245x2	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA95-01752B	ASSY SUB-PCB CONTROL;29M6,KS3A,AA95-0140	
...3	CN811	AA39-20179A	LEAD CONNECTOR-ASSY;,3(2)P,YFH800-150,S,	
...3	CNY01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,YBNH025-05,67096	
...3	CNY02	AA39-00100B	LEAD CONNECTOR-ASSY;,4P,YBNH250-04,35155	
...3	CY01	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
...3	LDY01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
⚠ ...3	PD811S	3711-004696	CONNECTOR-HEADER;NOWALL,3P,1R,10/5mm,ANG	
⚠ ...3	PD812S	3711-004697	CONNECTOR-HEADER;NOWALL,3P,1R,5/10mm,ANG	
...3	RMY01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3	SCREW	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	
...3	SCREW	6001-000057	SCREW-MACHINE;RH,+,M3,L6,ZPC(BLK),SWRCH1	S.N.A
⚠ ...3	SW811S	3403-001107	SWITCH-PUSH;250V,5A,DPST,-,KDC-A04	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		AA97-05552A	ASSY AUTO-SUB;29M6,KS3A	S.N.A
....4	DY01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DY02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZY01	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY02	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL01	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EL02	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EL03	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EL04	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	LY01	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4		AA41-00552A	PCB-CONTROL;29M6/25M6,CEM-1,1L,A,1.6T,24	S.N.A
...3		AA61-00530B	BRACKET-MASTER;25M6,29M6,SECC	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-07618L	ASSY PCB MAIN;CS29M6HP8X/ANB,KS3A,MORCCO	
...3	BOT	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	BOT2	AA39-00271A	LEAD CONNECTOR ASSY;,UL1185#26,UL/CSA,2P	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-	
...3	C820	2401-003076	C-AL;3300uF,20%,50V,WP,BK,18x35.5mm	
...3	CABLE	AA39-30007B	IF-CABLE;-,T,150mm,1365#26	
...3	CLAMP	AA65-30018A	CLAMP-WIRE;DONG-A,NYLON-66,-,-,-,DATL-60	S.N.A
...3	CLAMP	AA65-30104C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,W	S.N.A
...3	CLAMP	AA65-30105C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,5	S.N.A
...3	CLAMP	AA65-30109A	CLAMP-FBT;-,NYLON-66,V2,-,BLK,-	S.N.A
⚠ ...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;-,-,-,T1.5,-,SBHG-1,-	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	HC401	AA96-00291B	ASSY H/S;-,POWER,AA62-00051B,2SC5446 + F	S.N.A
....4		AA62-30177A	HEAT-SINK,PN;-,CUS-1,T1.0,-,KCV12D,-,-,1	S.N.A
....4		AA62-00051B	HEAT SINK-PS;-,-,-,SILVER,HOLE 34mm,ALL,	S.N.A
....4		AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,-,SBHG	S.N.A
....4		AA02-00007A	MICA;DPM-04,MICA,22x29x0.15mm	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		0502-001175	TR-POWER;2SC5446,NPN,200000mW,TO-3PL,BK,	
....4		0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
⚠ ...3	IC201S	AA98-00133B	ASSY-SIPADOSS MODULE;,100HZ,KS3A,SDA9401	
....4	C1	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C11	2203-001052	C-CERAMIC,CHIP;0.56nF,10%,50V,X7R,TP,160	
....4	C13	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C14	2203-001052	C-CERAMIC,CHIP;0.56nF,10%,50V,X7R,TP,160	
....4	C16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
....4	C17	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C18	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C19	2203-001052	C-CERAMIC,CHIP;0.56nF,10%,50V,X7R,TP,160	
....4	C2	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C20	2203-000552	C-CERAMIC,CHIP;0.02nF,5%,50V,NP0,TP,1608	
....4	C21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C22	2203-001256	C-CERAMIC,CHIP;0.008nF,0.25pF,50V,NP0,TP	
....4	C23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C24	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C25	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C26	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C27	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	C28	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
....4	C3	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	C32	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
....4	C33	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	C34	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
....4	C36	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
....4	C37	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	C38	2203-001603	C-CERAMIC,CHIP;220nF,10%,16V,X7R,TP,2012	
....4	C39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C4	2203-001052	C-CERAMIC,CHIP;0.56nF,10%,50V,X7R,TP,160	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C42	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C5	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C51	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C57	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C6	2203-000659	C-CERAMIC,CHIP;0.27nF,5%,50V,NP0,TP,1608	
....4	C7	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C8	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	C9	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
....4	CD3	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25pF,50V,NP0,TP,	
....4	CD4	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25pF,50V,NP0,TP,	
....4	CE1	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	CE2	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	CE3	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	CE4	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	CE5	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	CN64	3711-004778	CONNECTOR-HEADER;NOWALL,64P,2R,2MM,ANGLE	
....4	IC1	1204-001789	IC-VIDEO PROCESS;VPC3230D-B3,QFP,80P,787	
....4	IC2	1204-001858	IC-PICTURE PROCESS;SDA9401,QFP,64P,-,PLA	
....4	IC3	1204-001909	IC-VIDEO PROCESS;DDP3310B-F6,PLCC,68P,-	S.N.A
....4	JP1	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	L2	2702-001092	INDUCTOR-RADIAL;2.2uH,10%,6x4mm	
....4	L3	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
....4	L4	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
....4	P1	3711-004782	CONNECTOR-HEADER;NOWALL,32P,1R,1.778MM,S	
....4	P2	3711-004782	CONNECTOR-HEADER;NOWALL,32P,1R,1.778MM,S	
....4	PCB	AA41-00475A	PCB-SIPADOS TOP;CS29A5,FR-4,4L,A,1.6T,18	S.N.A
....4	PCB	AA41-00411A	PCB-SIPADOS BODY;CS29A5,FR-4,2L,A,1.6T,1	S.N.A
....4	R1	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4	R10	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4	R13	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
....4	R14	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
....4	R15	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
....4	R17	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	R19	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	R2	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4	R3	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4	R4	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4	R5	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4	R6	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
....4	R7	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	R9	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
....4	X2	2801-003432	CRYSTAL-UNIT;20.25MHZ,30PPM,28-AAM,13PF,	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	IC301	AA96-50381A	ASSY-H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30180B	HEAT-SINK,ES;-,A6063 EXTR.,2,WHT,70MM,-	S.N.A
...3	IC602	AA96-50369B	ASSY-H/S;-,-,AA62-30181F,TDA7297,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001064	IC-POWER AMP;7297,ZIP,15P,-,DUAL,32dB,PL	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181F	HEAT-SINK,ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
⚠ ...3	IC801S	AA96-50371F	ASSY H/S;-,PWM,AA62-30181H,KA3S1265RB,IC	S.N.A
....4		AA62-30181H	HEAT-SINK,ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		AA61-10386A	BRACKET-IC;-,SECC 100,T1.0,-,-,-,KA2S068	S.N.A
....4		AA13-00101A	IC HYBRID;KA3S1265RD,CN5039,5PIN,-50TO12	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	IC804	AA96-00243C	ASSY H/S;-,REGULATOR,AA62-00045A,KA7806,	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1203-000284	IC-POSI.FIXED REG.;7806,TO-220,3P,-,PLAS	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	IC901	AA97-07569A	ASSY MICOM;,KS3A,SDA555X,SIM-806HMA4,020	
....4	IC901	AA09-00041A	IC-MCU;,SDA555X-OTP,3.3V,-,128K,SDIP,-,4	S.N.A
...3	JA701	3722-000195	JACK-SCART;42P,-,SN,BLK,NO	
...3	L402	AA27-10004F	COIL-CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	L403	AA27-00015A	COIL-LINEARLITY;-,7.3UH,L81 DR15X18,-,-,	
...3	L408	AA27-00031A	COIL-HORIZ.WIDTH;-,140UH,AR 8X20,0.8MM,B	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q404	AA96-00437A	ASSY H/S;-,MAIN,AA62-00076A,IRF620,100Hz	S.N.A
....4		0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-00076A	HEAT SINK;100Hz,AL ,T1.0,10,40,-,-,-	S.N.A
...3	R228	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4M	
⚠ ...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ ...3	T444S	AA26-00082A	TRANS FBT;FUJ-29C002F(S),CT29A7DR,1.95mH	
⚠ ...3	T801S	AA26-00046A	TRANS SWITCHING;-,-,-,AC90~260V,DC135/16	
...3	TOP	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
...3	TOP1	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
⚠ ...3	TU02S	AA40-00084A	TUNER;TCPS3000PC16B(S),PAL ,181CH,38.9MH	
...3		AA97-03223A	ASSY ROBOT-MAIN;CS29M6HP8X/ANB,KS3A,MORC	S.N.A
....4	C405	2303-001015	C-FILM,PPF;5.5nF,5%,1.6kV,TP,29x9.5x17,2	
....4	C406	2303-001015	C-FILM,PPF;5.5nF,5%,1.6kV,TP,29x9.5x17,2	
....4	C407	2301-001338	C-FILM,MPE-PPF;0.68nF,5%,1.6kV,TP,28x7x1	
....4	C423	2301-001192	C-FILM,MPPF;820nF,5%,400V,TP,29x18.5x25.	
....4	C426	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
....4	C803	2401-003576	C-AL;470uF,20%,450V,GP,ST,35x45mm,10	
....4	C815	2401-003633	C-AL;220UF,20%,160V,GP,ST,22X25MM,10	
....4	CN501	3711-002641	CONNECTOR-HEADER;BOX,10P,1R,2.54mm,STRAI	
....4	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ 4	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CY802S	2201-002002	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,TP,16x	
⚠ 4	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
⚠ 4	IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
....4	IC601	1204-001661	IC-SOUND PROCESSOR;MSP3411G-A2,DIP,52P,-	
⚠ 4	IC803	1203-001697	IC-VOLTAGE REGULATOR;78R08,TO-220,4P,-,P	
....4	IC902	1103-001171	IC-EEPROM;L51DC,16KBit,DIP,8P,300MIL,10m	
....4	L405	AA27-00096A	COIL HORIZ. WIDTH;-,10.0mH,DR15 X 27.5,U	
....4	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ 4	LX801S	AA29-00012A	FILTER LINE NOISE;CS29A6PF8X/HAC,-,0.1MA	
⚠ 4	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 4	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ 4	PT801S	1404-000002	THERMISTOR-PTC;9ohm,20%,-,-,TR,RECT,-	
⚠ 4	RL801S	3501-001040	RELAY-POWER;12VDC,500mW,10A,1FormA,15mS,	
⚠ 4	TU01S	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
....4		AA97-04586A	ASSY AUTO-MAIN;CS29M6HP8X/ANB,KS3A,MORCC	S.N.A
.....5	C101	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C102	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C103	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C105	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C106	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C107	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C111	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C113	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
.....5	C115	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C116	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C201	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C202	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C205	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C207	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C208	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C209	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
.....5	C211	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C212	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C213	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
.....5	C214	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C215	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C218	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C219	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C220	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C228	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
.....5	C229	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C230	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
.....5	C231	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C233	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	C234	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	C235	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	C236	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	C237	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	C238	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C239	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C241	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C246	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
.....5	C247	2202-000849	C-CERAMIC,MLC-AXIAL;18pF,5%,50V,CH,TP,3.	
.....5	C248	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
.....5	C249	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C302	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
.....5	C303	2201-002022	C-CERAMIC,DISC;0.005nF,0.25pF,500V,NP0,T	
.....5	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
.....5	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
.....5	C306	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
.....5	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C401	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C403	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C404	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C408	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
.....5	C409	2301-001268	C-FILM,PPF;33nF,5%,630V,TP,20x11x17,7.5	
.....5	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C412	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
.....5	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C415	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C416	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
.....5	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C421	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
.....5	C424	2201-000132	C-CERAMIC,DISC;0.1nF,10%,500V,Y5P,TP,6.5	
.....5	C425	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
.....5	C601	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
.....5	C603	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C610	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
.....5	C611	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
.....5	C612	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
.....5	C613	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
.....5	C617	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C620	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C621	2401-002458	C-AL;1000uF,20%,35V,GP,TP,16x25,7.5	
.....5	C622	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
.....5	C623	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C624	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C625	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
.....5	C626	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
.....5	C627	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C628	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
.....5	C629	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C630	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C631	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C632	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
.....5	C634	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C636	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C637	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C638	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C639	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C640	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C641	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C642	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C643	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C644	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C645	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
.....5	C652	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C654	2201-000611	C-CERAMIC,DISC;0.056nF,5%,50V,NP0,TP,7x3	
.....5	C656	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
.....5	C657	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
.....5	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C704	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C707	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
.....5	C708	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
.....5	C805	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
.....5	C807	2301-001397	C-FILM,PPF;2.2nF,5%,1.2kV,TP,15x8.5x13.5	
.....5	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C809	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
.....5	C810	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
.....5	C811	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
.....5	C814	2201-000406	C-CERAMIC,DISC;0.27nF,10%,2kV,Y5P,TP,6.3	
.....5	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
.....5	C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5	C819	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C821	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C822	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C823	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C824	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C826	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
.....5	C827	2401-002212	C-AL;10uF,20%,25V,WT,TP,5x11,5	
.....5	C828	2201-000374	C-CERAMIC,DISC;0.22nF,5%,50V,NP0,TP,10.5	
.....5	C829	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C832	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C835	2401-002289	C-AL;470uF,20%,35V,WT,TP,10x20,5	
.....5	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C838	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C839	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C840	2401-002212	C-AL;10uF,20%,25V,WT,TP,5x11,5	
.....5	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
.....5	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C908	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
.....5	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C910	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
.....5	C911	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
.....5	C912	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C913	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C915	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C917	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C918	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C920	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C922	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C923	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C924	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	CN502	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
.....5	CN602	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CN702	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
.....5	CN704	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
.....5	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
.....5	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D203	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D204	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D205	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D206	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D208	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D209	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D210	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D211	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	D408	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5	D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D801	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
.....5	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D810	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D811	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D906	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	DZ201	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ202	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ203	0403-001321	DIODE-ZENER;MTZJ6.8C,6.66-7.01V,500mW,DO	
.....5	DZ204	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ205	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ304	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ305	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
.....5	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
.....5	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ602	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
.....5	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ802	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ803	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
.....5	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ805	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
.....5	DZ806	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ808	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	EL401	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL402	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL404	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL405	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL406	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL407	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL408	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL802	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL803	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL805	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL806	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL807	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL808	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL809	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL810	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL811	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EY301	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY302	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY303	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY304	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY401	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY402	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY403	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY404	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY405	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY406	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY407	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY408	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY409	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY410	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY411	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY412	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY413	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY414	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY415	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY416	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY417	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY418	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY419	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY420	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY421	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY422	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY423	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY424	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY425	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY426	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY427	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY428	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY429	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY430	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY431	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY432	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY433	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY434	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY435	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY436	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY437	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY438	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY439	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY440	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY441	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY442	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY443	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY446	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY447	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY502	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY601	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY602	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY603	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY604	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY701	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY702	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY801	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY802	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY803	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY804	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY805	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY806	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY807	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY808	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY809	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY810	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY811	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY812	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY813	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY814	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY815	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY816	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY817	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY818	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY819	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY820	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY822	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY823	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY824	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY825	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY826	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY827	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY828	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY829	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY830	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY831	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY832	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EY833	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY834	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY835	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY836	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY837	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY838	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY839	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY840	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY841	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY842	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY844	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY845	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY846	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY847	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY848	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY849	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY850	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY851	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY852	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY853	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY854	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY855	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY856	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY857	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY858	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY859	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY860	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY861	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
.....5	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 5	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 5	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
.....5	GT101	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT102	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT103	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT104	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT301	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT302	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT401	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT402	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT403	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT404	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT405	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT406	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT409	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT410	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT411	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT412	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT801	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT802	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT803	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT804	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT805	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT806	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	HIC201	AA13-00093A	IC HYBRID;-,DRGB001A,SIP,5P,-,TP	
.....5	HIC202	AA13-00093A	IC HYBRID;-,DRGB001A,SIP,5P,-,TP	
.....5	HIC203	AA13-00093A	IC HYBRID;-,DRGB001A,SIP,5P,-,TP	
.....5	HIC204	AA13-00093A	IC HYBRID;-,DRGB001A,SIP,5P,-,TP	
.....5	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
.....5	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
.....5	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
.....5	J401	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	J406	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	J901	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	J904	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	J919	2701-000183	INDUCTOR-AXIAL;39uH,5%,2.5x3.4mm	
.....5	J920	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
.....5	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L104	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L108	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L109	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L201	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L205	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
.....5	L206	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	L207	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L208	2701-000146	INDUCTOR-AXIAL;2.2uH,10%,2.5x3.4mm	
.....5	L209	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
.....5	L212	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
.....5	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
⚠ 5	L401	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
.....5	L406	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L412	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L604	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
.....5	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L701	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L702	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L711	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L804	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L807	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L905	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00168G	PCB-MAIN;CS29A6,FR-1,1L,G,1.6T,330X245,K	S.N.A
.....5	Q201	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q203	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
.....5	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q902	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R202	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R205	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R206	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R207	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R208	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R209	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R210	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R211	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R212	2004-000218	R-METAL;10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
.....5	R214	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R215	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R216	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R217	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R218	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R219	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R220	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R221	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R222	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R229	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R230	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R231	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R232	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R233	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	R234	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R235	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R236	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R237	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R238	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R240	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R241	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R242	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R243	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R244	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R245	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R246	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R247	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R248	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R249	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R250	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R252	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R253	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R254	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R301	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R302	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5	R304	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R305	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
.....5	R306	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
.....5	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R313	2004-001137	R-METAL;6.8Kohm,1%,1/8W,AA,TP,1.8x3.2m	
.....5	R314	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R315	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	R401	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R402	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R403	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
.....5	R404	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R407	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R409	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
.....5	R410	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
.....5	R411	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R412	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5	R415	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R417	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R418	2001-001159	R-CARBON(S);510OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R420	2004-004015	R-METAL(S);9.1Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5	R421	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R422	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R423	2004-004048	R-METAL(S);3.9Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5	R424	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R425	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
.....5	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
.....5	R433	2003-001042	R-METAL OXIDE(S);5.6Kohm,5%,2W,AF,TP,3.9	
.....5	R434	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
.....5	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R607	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R608	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R609	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R617	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R620	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R621	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R622	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R627	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R628	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R629	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R709	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R710	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R724	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R725	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R726	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R802	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R803	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R804	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R807	2006-001083	R-CEMENT;120ohm,5%,5W,CJ,TP,14x10x27mm	
.....5	R808	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R809	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R810	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R811	2004-001408	R-METAL(S);91Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R813	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R816	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R818	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R821	2004-001891	R-METAL(S);133Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R825	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
.....5	R828	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
.....5	R829	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
.....5	R831	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R832	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R833	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
.....5	R836	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
.....5	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R906	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R907	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R908	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R910	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R912	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R929	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R930	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R931	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R937	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R943	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R945	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R946	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R952	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 5	RX801S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP3.7x	
⚠ 5	RY801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP3.7x	
⚠ 5	RY802S	2002-001013	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP3.7x	
⚠ 5	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5	X601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
.....5	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
...3		AA95-01854A	ASSY SUB-PCB,VIDEO S/W;,KS3A,100HZ,AA95-	
....4	CNS01	3711-002704	CONNECTOR-HEADER;NOWALL,6P,1R,2.5mm,ANGL	
....4	CNS02	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	ICS01	1001-001114	IC-VIDEO SWITCH;TEA6425,VIDEO SWITCH ,DI	
....4		AA97-05269A	ASSY AUTO-SUB;KS3A,PAL,100Hz	S.N.A
.....5	CNS04	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
.....5	CS01	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS02	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS03	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS04	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS05	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS06	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	CS07	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
.....5	CS08	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	DZS01	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZS02	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	LS01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00153E	PCB-VIDEO SWITCH;CS29A6,FR-1,1L,E,1.6T,2	S.N.A
.....5	QS01	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	QS02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	QS03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	RS01	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS02	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS03	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS04	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS05	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS06	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS07	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS10	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS11	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS12	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS13	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS14	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA39-20010B	LEAD CONNECTOR-ASSY;,1P,YFH800-01,S,500,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA95-01832C	ASSY SUB-PCB,PIP;2T-PIP,KS3APAL,AA95-011	
....4	CNP01	3711-002709	CONNECTOR-HEADER;NOWALL,12P,1R,2.5mm,ANG	
....4	CNP02	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	CNP03	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CNP03A	AA39-00208A	LEAD CONNECTOR ASSY;,3P,67096-003,S,200M	
....4	HCP01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	XP01	2801-003432	CRYSTAL-UNIT;20.25MHZ,30PPM,28-AAM,13PF,	
....4		AA97-07013A	ASSY AUTO-PIP;2T-PIP,KS3A,PAL,AA95-01137	S.N.A
.....5	CP05	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	CP10	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	CP12	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	CP14	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5	CP17	2401-000667	C-AL;2.2uF,20%,50V,WT,TP,5x11,5	
.....5	CP19	2401-000667	C-AL;2.2uF,20%,50V,WT,TP,5x11,5	
.....5	CP23	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	CP25	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5		AA97-06916A	ASSY SMD-PIP;2T-PIP,KS3A,PAL,AA95-01137A	S.N.A
.....6	CP02	2203-000384	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,160	
.....6	CP03	2203-000384	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,160	
.....6	CP04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	CP06	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP07	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP08	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP09	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP11	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP13	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	CP16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP18	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	CP24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	CP30	2203-005030	C-CERAMIC,CHIP;470nF,+80-20%,50V,Y5V,TP,	
.....6	CP31	2203-005030	C-CERAMIC,CHIP;470nF,+80-20%,50V,Y5V,TP,	
.....6	DP01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP03	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP04	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DZP01	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DZP02	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DZP03	0403-001127	DIODE-ZENER;02DZ5.1,5.1,200mW,SOD-323,TP	
.....6	ICP01	1204-001658	IC-PICTURE PROCESS;SDA9489X-B22,SOP,28P,	
.....6	ICP02	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
.....6	LP02	2703-000392	INDUCTOR-SMD;10uH,5%,4.5x3.2x2.2mm	
.....6	LP03	2703-000392	INDUCTOR-SMD;10uH,5%,4.5x3.2x2.2mm	
.....6	PCB	AA41-00466B	PCB-PIP;CS29A6PF8X,CEM-3,2L,A,1.6T,180X2	S.N.A
.....6	QP01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	QP02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	QP03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	QP04	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	QP05	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	QP06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	QP07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	RP01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	RP02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	RP03	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP04	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP05	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP06	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	RP07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	RP13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	RP14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	RP15	2007-002425	R-CHIP;10HM,5%,1/16W,DA,TP,1608	
.....6	RP21	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	RP22	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	RP23	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6	RP24	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6	RP25	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	RP26	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	RP27	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6	RP28	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6	RP29	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	RP30	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	RP31	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP32	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP33	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP34	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP35	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP36	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	RP40	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	RP41	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	RP42	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	RP43	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	RP50	2007-000121	R-CHIP;820ohm,5%,1/16W,DA,TP,1608	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4		0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A
...3		AA95-01757K	ASSY SUB-PCB CRT;29M6(100HZ),KS3APAL,AA9	
....4	BOTZ	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4	CN501A	3711-002641	CONNECTOR-HEADER;BOX,10P,1R,2.54mm,STRAI	
....4	CN501E	AA39-00225A	LEAD CONNECTOR ASSY;,10P,67096-010,S,600	
....4	CN502E	AA39-20029K	LEAD CONNECTOR-ASSY;,7P,67096-007,S,400,	
....4	IC501	AA96-50151B	ASSY-H/S;-,AMP,AA61-10060A,TDA6111Q,-	S.N.A
.....5		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
.....5		6001-000057	SCREW-MACHINE;RH,+,M3,L6,ZPC(BLK),SWRCH1	S.N.A
.....5		6021-000222	NUT-HEXAGON;2C,M3,ZPC(YEL),SM20C 1	
.....5		AA61-10060A	BRACKET-TR;W3220,CUS-1 1/2H,T0.5,-,-,-,-	S.N.A
....4	IC502	AA96-50151B	ASSY-H/S;-,AMP,AA61-10060A,TDA6111Q,-	S.N.A
....4	IC503	AA96-50151B	ASSY-H/S;-,AMP,AA61-10060A,TDA6111Q,-	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	ICG01	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
....4	JA501	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
....4	QF04	AA96-00111A	ASSY-H/S;-,-,AA62-30013L,2SC2344,-	S.N.A
.....5		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
.....5		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
.....5		AA62-30013L	HEAT-SINK,ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
....4	QF05	AA96-00111B	ASSY-H/S;-,-,AA62-30013L,2SA1011,-	S.N.A
.....5		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
.....5		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
.....5		AA62-30013L	HEAT-SINK,ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
....4	QG01	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	R523	2008-000255	R-FUSIBLE(S);1.5ohm,5%,1W,AA,TP,3.9x10mm	
....4	SG502	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm MIN,	
....4	VA999	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4		AA97-05611A	ASSY AUTO-SUB;29M6(100HZ),KS3A,PAL	S.N.A
.....5	C502	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
.....5	C503	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C505	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
.....5	C506	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C508	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
.....5	C509	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C510	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
.....5	C511	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
.....5	C512	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
.....5	C513	2201-000723	C-CERAMIC,DISC;4.7nF,20%,3KV,Y5U,TP,16x5	
.....5	C514	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
.....5	C515	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
.....5	C516	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C518	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C519	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C520	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C521	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C522	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C523	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C526	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
.....5	CF01	2201-000180	C-CERAMIC,DISC;10nF,10%,50V,Y5V,TP,7x3,5	
.....5	CF02	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	CF03	2201-000376	C-CERAMIC,DISC;0.22nF,5%,50V,SL,TP,6.3x3	
.....5	CF04	2201-000653	C-CERAMIC,DISC;0.068nF,5%,50V,SL,TP,5x3,	
.....5	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
.....5	CF06	2201-000516	C-CERAMIC,DISC;4.7nF,+100-0%,500V,Y5U,TP	
.....5	CF07	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
.....5	CF08	2201-000604	C-CERAMIC,DISC;0.056nF,+100-0%,500V,SL,T	
.....5	CF10	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	CF11	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
.....5	CF12	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	CF14	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
.....5	CG01	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
.....5	CG02	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
.....5	CG03	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	CG04	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
.....5	CN502A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
.....5	CNF01	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
.....5	CNG01	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
.....5	D502	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D507	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	D508	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	D509	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	D510	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	D511	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	D512	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DF02	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	DF03	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
.....5	DF04	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DG01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DZ503	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
.....5	DZ504	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
.....5	DZ505	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
.....5	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
.....5	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
.....5	DZG501	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
.....5	EL81	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL82	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL83	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL84	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL85	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL86	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL87	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL88	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL89	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL90	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL91	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL92	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL93	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EL94	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
.....5	EY501	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	GT504	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT505	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT506	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GT508	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	L501	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
.....5	L503	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L504	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L505	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L506	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L507	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
.....5	LF01	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	LF02	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
.....5	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	LF05	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	PCB	AA41-00210D	PCB-CRT;CS29A6,FR-1,1L,D,1.6T,330x245,KS	S.N.A
.....5	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
.....5	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
.....5	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
.....5	QF01	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	QF03	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
.....5	QG02	0502-000244	TR-POWER;KSA940,PNP,1.5W,TO-220,-,40-14	
.....5	QG03	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
.....5	R501	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R502	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R503	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R505	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
.....5	R506	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R507	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R508	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R510	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
.....5	R511	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R512	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R513	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
.....5	R517	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R518	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
.....5	R519	2002-001009	R-COMPOSITION;2.7Kohm,10%,1/2W,AA,TP,3.7	
.....5	R521	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R522	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R526	2004-000500	R-METAL;2.7Kohm,1%,1/8W,AA,TP,1.8x3.2m	
.....5	R527	2004-000433	R-METAL;1Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
.....5	R542	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R543	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R544	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R546	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF02	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF03	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF04	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF05	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF06	2001-000989	R-CARBON;820KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF07	2001-000904	R-CARBON;620OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF08	2001-000313	R-CARBON;11KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF09	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF10	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF11	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF12	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RF13	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RF14	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RF15	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RF16	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RF17	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RF18	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
.....5	RF19	2003-001023	R-METAL OXIDE(S);120ohm,5%,2W,AF,TP,3.9x	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	RF20	2003-002214	R-METAL OXIDE(S);680ohm,5%,2W,AG,TP,3.9x	
.....5	RF21	2003-002214	R-METAL OXIDE(S);680ohm,5%,2W,AG,TP,3.9x	
.....5	RF22	2003-002214	R-METAL OXIDE(S);680ohm,5%,2W,AG,TP,3.9x	
.....5	RF23	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
.....5	RF24	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
.....5	RF25	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
.....5	RG01	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	RG02	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	RG03	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	RG04	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	RG05	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RG06	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RG07	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	RG08	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	SG501	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm MIN,	
.....5	SG503	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm MIN,	
.....5	SG504	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm MIN,	
.....5	SG505	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm MIN,	
...3		AA95-01734A	ASSY SUB-DYNAMIC FOCUS;29,KS3A,PAL,100H	
....4	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,-,EER2	
....4	LH02	AA27-40003L	COIL-HORIZ.WIDTH;-,1.0mH,DR14x20,2UEW0.4	
....4	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
....4	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,YFH800-03,S,200,	
....4		AA97-05261A	ASSY AUTO-SUB;29,KS3A,PAL,100Hz	S.N.A
.....5	EY01	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY02	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY03	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY04	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY05	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY06	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY07	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY08	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY09	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY10	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY11	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY12	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY13	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY14	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY15	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY16	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY17	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY18	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	EY19	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
.....5	GTH01	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GTH02	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	GTH03	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
.....5	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA65-30105A	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,1	S.N.A
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A

ASSY CPT

1	*	AA91-02220A	ASSY CPT;CS29M6HP8X/AWE	S.N.A
..2		AA91-02173Z	ASSY CPT;A68QCP891X004(C),29,0MG,ITC	S.N.A
...3		AA03-00082A	CRT-COLOR;A68QCP891X004(C),0mG,0.315mH,7	
..2		AA98-70011A	ASSY-TBC,WIRE(P);-,29INCH,NTSC,PAL,2P-WH	S.N.A
..2		AA27-20002Q	COIL-DEGAUSSING;-,29,14ohm,70T,L3300,E	

ASSY COVER REAR

1	*	AA90-02037E	ASSY COVER REAR;CS29M6HP8X/AWE	S.N.A
..2	CABBAC	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
..2		AA65-30008A	CLAMP-CORD;-,PE,HB,-,BLK,-	S.N.A
..2		AA64-02099C	CABINET-BACK;29M6,HIPS,HB,G4309	
..2		AA64-00894B	INLAY BACK;D2,D3,PS SHEET,T0.3,-,-,BLK,S	S.N.A
..2		AA60-00091P	SPACER-FELT;,FELT,500X10,BLK,T0.5	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER FRONT

1	*	AA90-01874E	ASSY COVER FRONT;CS29M6HP8X/AWE	S.N.A
..2	AV+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
..2	BRA+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+HP	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	
..2	CB+RJ	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	PCB+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	PCB+HP	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA91-00507A	ASSY HOLDER SPK;-,-,80HM/15W,-,ASSY HOLD	
..2		AA91-00777D	ASSY CABINET FRONT;,29M6 ASIA 100HZ,SVN1	
...3	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3	WR+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3		AA64-02102B	KNOB CONTROL;25M6,29M6,ABS,HB,G3676,SV10	
...3		AA64-02103B	WINDOW-RMC,LED;25M6,29M6,ACRYL,HB,CLEAR	S.N.A
...3		AA64-02104B	DECORATION-POWER;25M6,29M6,ABS,HB,WHT,SV	
...3		AA64-70117B	BADGE-BRAND;-,AL,-,-,L65,R2000,SILVER,SS	S.N.A
...3		AA65-00011C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,2	S.N.A
...3		AA65-30105A	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,1	S.N.A
...3		AA64-02100B	KNOB POWER;25M6,29M6,ABS,HB,G3676,IVN-11	
...3		AA61-00711B	HOLDER-PCB;29U1,U2,HIPS FV2,BK502(HB-PRO	S.N.A
...3		AA61-60003J	SPRING-CS;-,SUS304,-,-,OD6,N7,OD6,-,-,-	S.N.A
...3		AA63-00488B	COVER-CONTROL;29M6,ABS,HB,WHT,SVM6145+CL	S.N.A
...3		AA64-01506D	INLAY-AV;29K3,PVC-SHEET,T0.3,-,-,P/GRAY,	S.N.A
...3		AA64-02096E	CABINET-FRONT;29M6 M-EAST 100,HIPS,HB,G4	S.N.A
..2		AA65-00019A	CLAMP CORE-D,COIL;25-34,NYLON 66,V2,NTR	S.N.A
..2		AA65-30017A	CLAMP-D,COIL;-,NYLON-66,V0,-,NTR,DADH300	S.N.A
..2		AA60-00055A	SPACER-GUM,CRT;ALL MODEL,NTR RUBBER,-,-,	S.N.A
..2		AA61-00552B	HOLDER-PCB;29K3,HIPS,-,-,-,BLK,V0	S.N.A
..2		AA61-00813B	SUPPORT-CRT;25M6,29M6,HIPS,HB,NATURL	S.N.A
..2		AA61-10054A	BRACKET-CRATER;6277,STS304,T0.5,-,-,-,-	S.N.A

ASSY ACCESSORY

1	*	AA92-03246E	ASSY ACCESSORY;CS29M6HP8X/AWE	S.N.A
..2		AA68-01141C	MANUAL USERS;,FRE.(AFRICA),W/P100G,ALL1,	
..2		AA68-01015D	MANUAL USERS;,ENG,W/P100G,ALL1,B5,KS3A,4	
..2		AA59-00128D	REMOCON;-,TM58,DREAM-D3,40,L/GRAY,TTX,EX	
..2		AA39-40001B	CABLE-RCA;,1500MM	

MEMO